



12BL6

12BL6

REMOTE-CUTOFF PENTODE

7-PIN MINIATURE TYPE

For use in automobile radio receivers operating directly from 12-volt storage batteries

GENERAL DATA

Electrical:

Heater[•], for Unipotential Cathode:

Voltage range. . . . 10.0 to 15.9 dc volts

This voltage range is on an absolute basis. For longest life, it is recommended that the heater be operated within the voltage range of 11 to 14 volts.

Current (Approx.)

at 12.6 volts. . . . 0.15 amp

Direct Interelectrode Capacitances:^o

Grid No.1 to plate 0.006 max. μ f

Grid No.1 to cathode, grid No.3 & internal shield, grid No.2, and heater. 5.5 μ f

Plate to cathode, grid No.3 & internal shield, grid No.2, and heater. 4.8 μ f

Mechanical:

Operating Position Any

Maximum Overall Length 2-1/8"

Maximum Seated Length. 1-7/8"

Length, Base Seat to Bulb Top (Excluding tip). 1-1/2" $\pm$ 3/32"

Maximum Diameter 3/4"


Dimensional Outline. See General Section

Bulb T5-1/2

Base Small-Button Miniature 7-Pin (JETEC No.E7-1)

Basing Designation for BOTTOM VIEW 7BK

Pin 1-Grid No.1
Pin 2-Grid No.3,
Internal
Shield
Pin 3-Heater



Pin 4-Heater
Pin 5-Plate
Pin 6-Grid No.2
Pin 7-Cathode

AMPLIFIER — Class A₁

Maximum Ratings, Design-Center Values:

PLATE VOLTAGE. 30 max. volts

GRID-No.2 (SCREEN-GRID) VOLTAGE. 30 max. volts

GRID-No.1 (CONTROL-GRID) VOLTAGE:

Positive bias value. 0 max. volts

CATHODE CURRENT. 20 max. ma

PEAK HEATER-CATHODE VOLTAGE:

Heater negative with respect to cathode 30 max. volts

Heater positive with respect to cathode 30 max. volts

Characteristics with 12.6 Volts on Heater:

Plate Voltage. 12.6 volts

Grid-No.3 (Suppressor-Grid) Voltage. 0 volts

^{•,o}: See next page.

12BL6



12BL6

REMOTE-CUTOFF PENTODE

Grid-No.2 Voltage.	12.6	volts
Grid-No.1 Supply Voltage	0	volts
Grid-No.1 Resistor (Bypassed).	2.2	megohms
Plate Resistance (Approx.)	0.5	megohm
Transconductance	1350	μ nhos
Plate Current.	1.35	ma
Grid-No.2 Current.	0.5	ma
Grid-No.1 Voltage (Approx.) for trans- conductance of 10 μ nhos.	-6	volts
Grid-No.1 and Grid-No.3 Voltage (Approx.) for transconductance of 10 μ nhos	-5	volts

Maximum Circuit Values:

Grid-No.1-Circuit Resistance	10 max.	megohms
--	---------	---------

- Operation of heater in series with other heaters is not recommended.
- With external shield JETEC No.316 connected to cathode.

OPERATING CONSIDERATIONS

The *maximum ratings* in the tabulated data for the 12BL6 are working design-center maximums established according to the standard design-center system of rating electron tubes. Tubes so rated will give satisfactory performance in storage-battery-operated equipment provided the following stipulations are observed:

In the case of storage-battery-with-charger supply or similar supplies, the normal battery-voltage fluctuation may be as much as 35 per cent or more. This fluctuation imposes severe operating conditions on tubes. Under these conditions, the equipment should be designed so that 90 per cent of the design-center maximum value of plate voltage and grid-No.2 voltage is never exceeded for a battery-terminal potential of 13.2 volts. Although the operating voltages of the 12BL6 in this service will, at times, exceed the design-center maximum values, satisfactory performance with probable sacrifice in life will be obtained.